

MULTIMETRY

	Analogové multimetry				Digitální multimetry		
	1109S	1110	1018H*	1019R	1030	2000/2001	2012R
Vzhled přístroje							
DCV	0.1 - 1000V	3 - 600V	400mV - 600V	600mV - 600V	400mV - 600V	340mV - 600V	600mV - 600V
ACV	10 - 1000V	30 - 600V	4 - 600V	6 - 600V	4 - 600V	3.4 - 600V	6 - 600V
DCA	50uA - 250mA	60uA - 300mA	-	-	-	60A(2000) 100A(2001)	60/120A
ACA	-	-	-	-	-	60A(2000) 100A(2001)	60/120A
Odpor	✓	✓	✓	✓	✓	✓	✓
Bzučák spojitosti	-	✓	✓	✓	✓	✓	✓
Kapacita	-	-	✓	✓	✓	-	✓
Frekvence	-	-	✓	-	✓	✓	✓
Podsvícení	-	-	-	-	✓	-	-
Záznamová paměť	-	-	-	-	-	-	-
Kategorie bezpečnosti	-	CAT III 300V CAT II 600V	CAT III 300V	CAT III 300V CAT II 600V	CAT III 600V	CAT III 300V CAT II 600V	CAT III 300V CAT II 600V
Zdroj napájení	R6x2/6F22 x 1	R6 x 2	LR44 x 2	CR2032 x 1	LR44 x 2	R03/LR03 x 2	R03/LR03 x 2
Rozměry (V)x(Š)x(H)mm	150x100x47	140x94x39	107x54x10	126x85x18	190x39x31	128x84x24(2000) 128x92x27(2001)	128x92x27
Váha (cca.)	330g	280g	70g	135g	100g	210g(2000) 220g(2001)	220g

H*: Hard case type

	Digitální multimetry					
	1009	1011/1012	1020R	1021R	1051/1052	1061/1062
Vzhled přístroje						
DCV	400mV - 600V	600mV - 600V	600mV - 1000V	600mV - 600V	600mV - 1000V	50mV - 1000V
ACV	40mV - 600V	6 - 600V	600mV - 1000V	600mV - 600V	600mV - 1000V	50mV - 1000V
DCA	400uA - 10A	600uA - 10A	-	6A - 10A	600uA - 10A	500uA - 10A
ACA	400uA - 10A	600uA - 10A	-	6A - 10A	600uA - 10A	500uA - 10A
Odpor	✓	✓	✓	✓	✓	✓
Bzučák spojitosti	✓	✓	✓	✓	✓	✓
Kapacita	✓	✓	✓	✓	✓	✓
Frekvence	✓	✓	✓	✓	✓	✓
Podsvícení	-	-	✓	✓	✓	✓
Záznamová paměť	-	-	-	-	✓(1052)	✓
Kategorie bezpečnosti	CAT III 300V	CAT III 300V CAT II 600V	CAT IV 300V CAT III 600V CAT II 1000V	CAT IV 300V CAT III 600V	CAT IV 600V CAT III 1000V	CAT IV 600V CAT III 1000V
Zdroj napájení	R6 x 2	R6/LR6 x 2	R03/LR03 x 2	R03/LR03 x 2	R6/LR6 x 4	R6/LR6 x 4
Rozměry (V)x(Š)x(H)mm	161x82x50	161x82x50	155x75x40	155x75x40	192x90x49	192x90x49
Váha (cca.)	280g	280g	250g	250g	560g	560g